



DES CRIP TION

MEGA-LITE has re-amped the infamous scanner fixtures by creating the Stinger Scan-150. Designed to be more powerful and deliver a high output, this fixture features a 150W single color LED.

Packed with 8 colors+open, 7 removable, bi-directional, indexing rotation gobos and 4-facet, rotatable, indexing prism, the Stinger Scan-150 is ideal for creating dramatic eye-catching effects. Between the mechanical focus, 180° pan and 40° tilt it can deliver sharp optics and mid-air looks at a high-speed.

With a 15° lens angle, it produces impressive beams of light that are designed to deliver striking aerial effects. The fast mirror pace is suited for high energy music and high impact lighting that compliments other moving head effects.

Features.

POWERFUL

STINGER

MEGA®

i i fii i

Designed to be more powerful and deliver a high output, this fixture features a powerful 150W single color LED.



FAST PAN & TILT

The 180° and and 140° tilt can deliver high-speed optics and mid-air looks for dramatic eye-catching effects.



EFFECTS

The fixture is packed with 8 colors+open, 7 removable, bi-directional, indexing rotation gobos and a 4-facet, rotatable, indexing prism.

It produces impressive beams of light that are designed to deliver striking aerial effects.

STREET

Specifications.

Source:

Led Type:	150W SINGLE COLOR
21	

Optical System:

Lens Angle:	15°
Focus:	MECHANICAL FOCUS

Effects:

Colors:8 COLORS + OPENRoatating Gobos:7 REMOVABLE, BI-DIRECTIONAL, INDEXINGPrism:4-FACET, ROTATABLE, INDEXING

Control & Programing:

RDM	YES
Display:	DIGITAL
Protocol:	DMX 512
DMX Channels:	2 MODES OF OPERATION

Movement: :

180°	
40°	
inections:	
PANEL MOUNTED POWER CON (TYPE) IN & OUT	
PANEL MOUNTED 5PIN XLR CONNECTOR IN & OUT (3 PIN OPTIONAL)	
ELECTRONIC AUTO SWITCHING 100V-240V 50/60HZ	
WATTS: 272W AMPS: 2.3A F5A 250V	

Dimensions:

Fixture Size:	10.5" X 6.5" X 18.5"
Fixture Weight:	16.5 lb (7.5 kg)
Packaged Size:	23.25" X 12" X 20"
Packaged Weight:	20 lb (9 kg)



18662 Bandera Rd Helotes, TX 78023

Phone (210)684-2600 / Fax (210)855-6279 info@mega.lighting

mega.lighting