

MM



HAZE2ENGINE™





DESCRIPTION

The Haze 2 Engine offers versatile functionality with its adjustable output direction feature, allowing you to create various haze effects tailored to different events. With means of control including a convenient 2 button remote which gives you complete flexibility in how you control your unit.

These features along with the unit's quiet mode make the Haze 2 Engine an extremely versatile unit.



Features.



ADJUSTABLE DIRECTION

The Haze 2 Engine has two adjustable gates that can be used to change the direction the haze flows out of the unit creating different effects for different events.



WIRELESS CONTROL

The Haze 2 Engine can also be controlled via 2 button remote control giving you more flexibility in how you control this unit.



QUIET MODE

The unit is equipped with a quiet mode engineered for theatrical and intimate venues, ensuring an immersive experience for both performers and audiences alike.

Specifications.

Mechanical Specifications:

Housing:	Sheet Metal
Mounting System:	Rubber feet for Floor Mounting
Power Connection:	Panel: Seetronics SAC3MPX Panel Mount. Cable: Seetronics SAC3FX to Nema 5/15.
Signal Connection:	3 and 5 Pin XLR In and Out
Output Direction:	Forward and Upwards gates
Tank Size:	42oz
Wireless Controller:	Wireless handheld on/off controller
Manual Engage:	Yes

Control System:

Operating Mode:	DMX, Manual Settings Via Display, Wireless Remote on/off controller, Manual Engage Button.
Protocol:	DMX 512
Channel Modes:	2 Channel Mode Volume, Fan Speed
DMX-512:	Yes

Electrical Specifications:

Power Input:	110V 60hz
Fuse:	F10 250V
Heat Source Watts:	900W
Power Consumption:	927 Watts 8 Amps @110V
Fan Speed:	Controlled Via Display and DMX
Haze Output:	Controlled Via Display and DMX
Haze Volume:	9,000 CuFT/Min
Heat Up Time:	1 min 40 sec from cold start

Dimensions:

Fixture Size:	18.5" X 6.36" X 9.5"
Fixture Weight:	12lb
Packaged Size:	21.5" X 9" X 10.75"
Packaged Weight:	14lb

MEGA **LITE**®

WWW.MEGA.LIGHTING

18662 Bandera Rd
Helotes, TX 78023

Phone (210)684-2600 / Fax (210)855-6279
info@mega.lighting

m e g a . l i g h t i n g