



FOLLOWBOT 1000w LED





FOLLOWBOT 1000W LED

DES CRIP TION

Unleash the Followbot 1000W LED, an empowering follow spot LED fixture that elevates your lighting game. With its versatile color wheel and refined CTO wheel, it offers a spectrum of vibrant spotlights and precise color temperature control.

Complete with a built-in iris, seamless dimming, and a diffusion filter, it's the ultimate tool for precision lighting in any space.



Features.



COMPACT BUILD

This fixture is designed with a compact build, weighing in at just 75 lbs; This lightweight powerhouse is your ticket to a new level of lighting mastery.



POWERFUL LED OUTPUT

With its powerful 1000W LED technology, this fixture empowers you to illuminate any stage or event with unmatched precision and brilliance.



DMX CONTROL

The convenient DMX rail-mounted controller allows for effortless management of intensity, color, zoom, and strobe control via a DMX console. Elevate your lighting with seamless DMX control capabilities.



**Shine bright like a
diamond in the stage**

Specifications.

Mechanical Specifications

IP Rating:	20
Housing:	Extruded Aluminum, Plastic Bezel
Fastening System:	Tilt Yoke with Follow Spot Stand
Power Connection:	Seetronics SAC3MPA Input (Nema 5-15 to SAC3FCA, Cable Included)
Zoom:	3° to 6°
Focus:	Electronic Focus
Iris:	Electronic Iris
Strobe:	Strobe Control (only via DMX)
Color Wheel:	Seven (7) Colors
CTO:	Three (3) Filters Open: 8162K CTO 1: 6386K CTO 2: 5280K CTO 3: 3351K
Diffusion:	One (1) Diffusion Filter
Static Gobo:	One (1) Gobo Slot (Non-Rotational)
Gobo Size:	39.5mm
Gobo Image Size:	23.5mm
Gobo Max Thickness:	3mm

Electrical Specifications

Light Source:	One (1) 1000W LED
Power Supply:	Electronic 100-240V AC 50/60Hz
Power Consumption:	1109 Watts / 10.6 Amps @110
Power Factor:	0.98

Control Systems

Operation Method:	Mounted Scene Recorder & DMX Controlled via XLR Input
Display:	LCD
DMX Connection:	5-Pin XLR In & Out
Channel Mode:	8CH: Dimmer, Strobe, Iris, Color, CTO, Zoom, Focus, Diffusion

Size and Weight

Fixture Size & Weight:	44.5" x 12.91" x 19.13" & 75lbs
Packaged Size & Weight:	49.5" x 18.5" x 23" & 93lbs

MEGA **LITE**®

WWW.MEGA.LIGHTING

18662 Bandera Rd
Helotes, TX 78023

Phone (210)684-2600 / Fax (210)855-6279
info@mega.lighting

m e g a . l i g h t i n g