

baby
color H84





DESCRIPTION

The Baby Color H84 is an ultra-compact, bright color-changing fixture. Equipped with 7 12-watt LEDs, the output of the Baby Color H84 contends with the output of larger fixtures. The RGBWAUV LEDs produce a wide range of vibrant colors with the ability to add UV for an eerie hue effect. The fixture has a 20° beam angle and comes with a diffuser that increases the beam angle to 25°.

The Baby Color H84 is controllable via DMX 512 and has strobe, macro, and dimmer effects. It has a double mounting yoke so it can be set upon the floor or hung from a structure. It has a digital display designed for ease of use and is equipped with power con in and out and 5-pin XLR connection inputs and outputs



Features.



COMPACT

This compact, powerful fixture is just five pounds, making it ideal for touring or permanent installations.



RGBWAUV

Seven 12-Watt RGBWAUV LEDs allow for color mixing with Red, Green, Blue, White, Amber, and UV.



EFFECTS

Using DMX 512, create dimmer, strobe, and macro effects.

**The Baby Color H84 is
an ultra-compact, bright
color-changing fixture.**



Specifications.

Source:

Led type: 12W LEDS

Optical System:

Led Quantity: 7
Led Angle: 20°
Diffusion Beam Angle 25°

Control & Programing:

Display: DIGITAL
Protocol: DMX 512
DMX Channels: 5 MODES OF OPERATION
Control options: DISPLAY INDIVIDUAL COLOR CONTROL

Rigging:

Installation System: DOUBLE MOUNTING YOKE

Electrical & Connections:

Power Connection: POWERCON TYPE IN AND OUT
DMX Connectors: 5 PIN XLR CONNECTORS IN AND OUT
Power Supply: 110V-240V 50/60HZ
Power Consumption: 57 WATTS | .77 AMPS
Ballast: ELECTRONIC AUTO SWITCHING

Dimensions:

Fixture Size: 8.12" X 4.30" X 7.63"
Fixture Weight: 5 lb (2.27 kg)
Packaged Size: 10" X 9.25" X 6.5"
Packaged Weight: 7 lb (3.18 kg)



MEGA **LITE**[®]

WWW.MEGA.LIGHTING

18662 Bandera Rd
Helotes, TX 78023

Phone (210)684-2600 / Fax (210)855-6279
info@mega.lighting

m e g a . l i g h t i n g