

COLOR PICK

LED PAR 0190



COLOR PICK
LED PAR Q190



DESCRIPTION



The Red, Green, Blue, Warm White Color Pick LED Par Q190 is a color changing par fixture equipped with nineteen 10W LEDs. With a 25° fixture lens it can produce smooth wide wash color combinations. The 4 elements of control allow users to create different individual or grouped effects, including individual control of the center, second circle and two outer circle groups, creating eye-catching patterns.

The pre-programmed scenes provide flexibility for stand alone operations and eye candy effects. Equipped with a double mounting yoke, the unit can be rigged or grounded for versatile use. With a competitive price point, this unit was designed as an economical options for DJ's or venue up-lights.

Get colorful with the Color Pick LED Par Q190

Features.



COLORFUL

Featuring Red, Green, Blue and Warm White color mixing, it can create numerous color combinations



NINETEEN LEDS

This unit features a total of nineteen 10W R, G, B, WW LEDs that can be used to create individual or grouped effects.



SEGMENT CONTROL

The 4 segments of control allow users to create different individual or grouped effects, including individual control of the center, second circle and two outer circle groups, creating eye-catching patterns.



Get colorful with the Color Pick LED Par Q190

Specifications.

Source:

Led Type:	RED, GREEN, BLUE & WARM WHITE
LED QTY:	19
Each Led Watt:	10W

Optical System:

Fixture Lens Angle:	25°
---------------------	-----

Effects:

Color Temp on WW:	2958K
CRI:(WARM WHITE)	75
Segment Control:	4

Control & Programing:

DMX:	DMX 512 USITT STANDARD
DMX Channels:	4 MODE OF OPERATION
RDM:	YES
Operating Mode:	Stand Alone 255 STEP DIMMER SETTING VIA DIPLAY.

Rigging:

Installation System:	MOUNTING YOKE WITH KICK STAND
----------------------	-------------------------------

Electrical & Connections:

Power Input:	110-240V AC 50/60 HZ
Power Consumption:	155W 2.06A
Max Power Link:	7 UNITS @ 110V 14 @ 220V
Power Connection:	POWER CON TYPE IN & OUT
Signal Connection:	5 PIN XLR IN & OUT

Dimensions:

Fixture Size:	11.12" X 9" X 9.87"
Fixture Weight:	6.5 lb
Packaged Size:	11.5" X 11.5" X 12"
Packaged Weight:	8 lb



MEGA **LITE**[®]

WWW.MEGA.LIGHTING

18662 Bandera Rd
Helotes, TX 78023

Phone (210)684-2600 / Fax (210)855-6279
info@mega.lighting

m e g a . l i g h t i n g